


4064200 - 10VA 4064205 - 20VA
4064206 - 40VA 4064207 - 35VA
4063911 - 100VA 4063912 - 200VA
4063913 - 350VA 4063925 - 50VA

Disconnect from mains supply before replacing the fuse or the lamp.
Vor dem Einsetzen der Sicherung oder der Lampe Spannungsfreiheit herstellen.
Débrancher le secteur avant de remplacer le fusible ou l'ampoule.
Desconectar del suministro de la red, antes de realizar la sustitución del fusible o de la lámpara.
Voor het vervangen van lamp of zekering, eerst netspanning uitschakelen.
Koppla bort spänningen före byte av en säkring eller en lampa.



Switch Off
Abschalten
Débrancher
Desconectar
Uitschakelen
Stäng av

All Transformers are Class II Safety Transformers made in accordance with VDE 0551-EN60 742.

Specifications:

4064200 - 10VA

Dimensions (mm) = (L x W x H) 140 x 121 x 60
Weight = 2.5kg
Primary: 240V 50/60Hz
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Secondary: 12V
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Capacity: 10VA (1 x 10W)
Fuse: Primary Only - t0.16A/250 D - Replaceable

4064205 - 20VA

Dimensions (mm) = (L x W x H) 140 x 121 x 60
Weight = 2.5kg
Primary: 240V 50/60Hz
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Secondary: 12V
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Capacity: 20VA (2 x 10W)
Fuse: Primary Only - t0.16A/250 D - Replaceable

4064206 - 40VA

Dimensions (mm) = (L x W x H) 140 x 121 x 60
Weight = 2.7kg
Primary: 240V 50/60Hz
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Secondary: 12V
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Capacity: 40VA (2 x 20W)
Fuse: Primary Only - t0.4 A/250 D - Replaceable

4064207 - 35VA

Dimensions (mm) = (L x W x H) 140 x 121 x 60
Weight = 2.5kg
Primary: 240V 50/60Hz
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Secondary: 12V
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Capacity: 35VA (1 x 35W)
Fuse: Primary Only - t0.315A/250 D - Replaceable

4063911 - 100VA

Dimensions (mm) = (L x W x H) 170 x 131 x 80
Weight = 3.2kg
Primary: 240V 50/60Hz
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Secondary: 12V
2 x Cable entry Pg11
2 x Terminal block 2 x 2.5 C.S.A.
Capacity: 100VA (2 x 50W)
Fuse: Primary Only - t1.0A/250 D - Replaceable

4063912 - 200VA

Dimensions (mm) = (L x W x H) 186 x 131 x 104
Weight = 2.5kg
Primary: 240V 50/60Hz
1 x Cable entry Pg13.5
1 x Terminal block 2 x 2.5 C.S.A.
Secondary: 12V
2 x Cable entry Pg13.5
2 x Terminal block 4 x 4.0 C.S.A.
Capacity: 200VA (2 x 100W)
Fuse: Primary Only - t1.6A/250 D - Replaceable

4063913 - 350VA

Dimensions (mm) = (L x W x H) 215 x 175 x 110
Weight = 7.2kg
Primary: 240V 50/60Hz
1 x Cable entry Pg13.5
1 x Terminal block 2 x 2.5 C.S.A.
Secondary: 12V
1 x Cable entry Pg13.5
1 x Terminal block 4 x 4.0 C.S.A.
Capacity: 350VA (2 x 175W)
Fuse: Primary Only - t2.5A/250 D - Replaceable

4063925 - 50VA

Dimensions (mm) = (L x W x H) 140 x 121 x 60
Weight = 2.8kg
Primary: 240V 50/60Hz
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Secondary: 12V
1 x Cable entry Pg11
1 x Terminal block 2 x 2.5 C.S.A.
Capacity: 50VA (1 x 50W)
Fuse: Primary Only - t0.4A/250 D - Replaceable

Suitable for use indoors
Geeignet für Innenanwendung
Pour un usage interne
Adecuada para uso en interiores
Geschild voor gebruik binnen
Lämplig för inomhusbruk



Replace any cracked protective shield.

Dieses symbol bedeutet, dass defekte Schutzgläser sofort ersetzt werden müssen.

Ce symbole indique que vous devez remplacer tout verre de protection fêlé.

Este símbolo indica que hay que reemplazar filtros en caso de rotura o desperfectos.

Dette symbolet indikerer at alle ødelagte (sprukne) sikkerhetglass må skiftes.

Valaisinta ei saa käyttää ilman suojalasia vioitunut suojalasi on vaihdettava uuteen ennen valaisimen käyttöön ottoa.

< Millimetres >



This Electrical Product
MUST be recycled.



07.08

Concord

Avis Way Newhaven East Sussex BN9 0ED
T 0870 606 2030 F 01273 512 688 email: information@concordmarlin.com

