

For use with Marlinea Luminaires fitted with PIR control.
This controller can be used to manually override the automatic mode of the PIR sensor.
In the manual mode the light sensing function is disabled but the presence detection is unaffected.

The manual override functions are:-

ON = MAXIMUM LIGHT OUTPUT
OFF = LUMINAIRE SWITCHED OFF
UP = INCREASE LIGHT LEVEL
DOWN = DECREASE LIGHT LEVEL

The luminaire can be reset to automatic mode using the button marked AUTOMATIC.
The factory settings of the PIR control can only be permanently overwritten by using the Programmer MPA 300.

The factory settings of the PIR control are:-

- MAXIMUM LIGHT LEVEL (**MAX** 1-100%)
- TIME DELAY TO SWITCH OFF WHEN VACANT (**20 MINUTES** 30 SECONDS - 60 MINUTES + CONTINUOUS)
- PRESENCE DETECTION (**ACTIVE** INACTIVE)
- SWITCHING OFF LUMINAIRE IN EXCESS BRIGHTNESS (**YES** NO)
- LIGHT LEVEL WHEN VACANT (**OFF** LOW CONTINUOUS)
- STARTING BEHAVIOUR (**ON** OFF)
- WHETHER CONTROLLER OVERRIDE SETTINGS ARE PERMANENT (**NO** YES)


Default values are indicated in **BOLD TYPE**

Full details of their function are included with the Programmer MPA 300.

POWER - 2*LR03/AAA/1.5V BATTERY CELLS

Suitable for use indoors
Geeignet für innenanwendung
Pour un usage interne

Adecuada para uso en interiores
Geschikt voor gebruik binnen
Lämpig för inomhusbruk

 This Electrical Product
MUST be recycled.

