


4148583 4158292 4158293 4164374 4143585
 4158295 4158297 4160778 4158291 4162559
 4043269 4044143 4044144 4044145 4044146
 4044147 4043268 4044141 4044142 4156891
 4060611 4060613 4060615 4060610 4060612
 4060614 4060617 4060619 4060621 4060623
 4060625 4060627 41609524 4160954 4161599
 4060616 4060618 4060620 4060622 4060624
 4060626 4161067 4162158 4165702 4037148
 4037368 4037372 4037373 4037530 4037531
 4037532 4037533 4037534 4037954 4037955
 4037957 4037970 4037002 4038003 4038004
 4056615 4056640 4056649 4056679 4056683
 4062814 4062816 4062817 4140533 4143584
 4143586 4148566 4148567 4148568 4148573
 4148574 4148575 4148576 4148578 4148581
 4148584 4148588 4148589 4156892 4156893
 4158289 4158294 4158296 4158298 4160863
 4160864 4162160 4163565 4164079 4164080
 4164268 4164271 4164382 4164524 4164690
 4164944 4164992 4164999 4165094 4165336
 4165392 4165499 4165507 4165527 4165570
 4165832 4165904 4166054 4166082

Disconnect from mains supply before replacing the fuse or the lamp.
 Vor dem Einsetzen der Sicherung oder der Lampe Spannungsfreiheit herstellen.
Débrancher le secteur avant de remplacer le fusible ou l'ampoule.
 Desconectar del suministro de la red, antes de realizar la sustitución del fusible o de la lámpara.
Voor het vervangen van lamp of zekering, eerst netspanning uitschakelen.
 Koppla bort spänningen före byte av en säkring eller en lampa.



Switch Off
 Abschalten
Débrancher
 Desconectar
Uitschakelen
 Stäng av

This luminaire is suitable for interior ceiling or wall mounting to a 50.8mm conduit box or directly to a mounting surface and can be semi-recessed using a Recessing Kit.

Installation should be carried out by a suitably qualified person in accordance with good electrical practice and with the appropriate national wiring regulations.

Switch off mains electrical supply before commencing installation.

Installation Procedure

Carefully lever out diffuser (E).

Check rating marked on label (B) conforms with mains electrical supply.

Partially screw suitable M4 screws in conduit box or alternatively prepare suitable fixings in mounting surface at 192mm centres for outrigger fixing.

NOTE: Gallery is marked 'TOP' for wall fixing.

Fit grommets (H) supplied in gallery.

Pass mains supply cable, control unit cable and LED cable, if applicable, through grommets.

Secure gallery (A) to conduit box or to mounting surface using suitable fixing screws.

Cover mains supply leads with silicone sleeving (G) supplied and connect to their respective terminals in terminal block (F).

For remote emergency types, connect control unit cable leads in respectively marked terminals in terminal block (K) and secure cable in clamp (J). Connect LED cable leads in respectively marked terminals in terminal block (M) and secure cable in clamp (L). Refer to remote control unit Instruction Sheet to unit connections.

Fit appropriate lamp as indicated on label (B) by pushing it firmly into lampholder (C).

Ease diffuser (E) into gallery rim ensuring it is held concentrically by the three retaining clips (D).

WARNING: Due to high starting voltage required to ignite lamp, MICC cable must not be used for luminaire to power module connection.

NOTE: This luminaire should be cleaned using warm soapy water and a soft cloth. Ensure luminaire is switched off during cleaning.

Dispose of lamps in accordance with manufacturer's instructions.

Suitable for use indoors
 Geeignet für Innenanwendung
Pour un usage interne
 Adecuada para uso en interiores
Geschikt voor gebruik binnen
 Lämpig för inomhusbruk



Replace any cracked protective shield.

Dieses symbol bedeutet, dass defekte Schutzgläser sofort ersetzt werden müssen.
Ce symbol indique que vous devez remplacer tout verre de protection fêlé.

Este símbolo indica que hay que reemplazar filtros en caso de rotura o desperfectos.


Dette symbolet indikerer at alle ødelagte (sprukne) sikkerhetglass må skiftes.

Valaisinta el saa käyttää ilman suojalasia vioitunut suojalasi on vaihdettava uuteen ennen valaisimen käyttöön ottoa.



Removing Diffuser

1. Press down. 2. Push to one side. 3. Lever out



Fitting Diffuser

1. Flex in. 2. Insert under rim. 3. Centralise

< Millimetres >

This Electrical Product **MUST** be recycled.



03.08